Two-way Radio



DL-T586s

Professional FM Transceiver

Main Features

- 400-470MHz
- Power Output 5W
- Scrambler
- 16 Channels Capacity
- CTCSS/DCS Support Non-standard input
- Scanning
- Chinese/English Voice Report
- Compandor
- Battery Save
- VOX Function
- Wide/Narrow Bandwidth
- OTA

General Specification		Transmitter		Receiver	
Frequency Range	UHF 400-470MHz	Output Power	5W	Sensitivity	-123dBM@25K
RF Output Power	High Power≤5W	Modulation	F3E	Selectivity	≤-65dB
Channels	16 Channels	Spurious and Harmonics	-65dB	Intermodulation	≤-55dB
Channel Spacing	Wide:25kHz, Narrow: 12.5kHz	FM Noise	≤-45dB	SNR	≥45dB
CTCSS/DCS	50 CTCSS/105 DCS	Audio Distortion	≤5%	Rated Audio Output Power	750mW
Antenna Impedence	50Ω			Rated Audio Distortion	≤5%
Working Voltage	DC7.4V				
Battery Type	7500mAh Li-ion Battery				
Dimension(excluding antenna)	108(H)*58(W)*30(D)mm				
Weight(Battery, Antenna included)	About 230g				

(REMARK: The specifications of the product may be modified for improvement without notice)

Standard Accessories


Antenna


Battery


Belt clip


The slin


Charging Dock